Modular belt conveyor WL374X

Contents

System information	11
Conveyor sections	
Modular Belts - Introduction	119
Modular belts	12
Conveyor Beams - Introduction	12
Conveyor frame components	124
Slide rail	12
End Drive Units - Introduction	12

Drive units – configuration strings	127
End drive units	128
Idler end units – Introduction	130
Idler units	130
Plain Bends - Introduction	131
Vertical bends	133
Support System Modules - Introduction	134

System information



System overview

FlexLink's newly developed stainless steel conveyor is designed to fit into demanding primary and secondary packaging applications. It addresses important aspects of today's packing processes, such as being easy to clean, smooth handling of products, safe for operators, robust design, long life, and easy to maintain with a low cost of ownership.

The modularized and standardized design ensures fast set up, and facilitates rapid future extensions and changes.

Technical specifications

Maximum speed	40 m/min
Maximum conveyor length	20 m
Max single item weight	
Total load on a conveyor	300 kg
Max product weight per belt pitch	
Max plain bends per conveyor	
	total)
Max permissible pull force (with	
bends)	1000 N
Max permissible pull force (without	
bends)	. 1200 N

WL 222X

WL 273X

WL 526X


WL 678X

CSX

GRX


FSTX

TR APX




7. End drive units

The modular plastic belt conveyor in five widths -222, 273, 374, 526 and 678 mm - can be built as straight sections or in S, U or L-shape with 30, 45, 60, 90° (180° only for 222 and 273) horizontal bend, or combinations thereof. Vertical bends are available in 5° (3° only for 222 and 273) positive or negative.



Modular Belts - Introduction



Modular belt, Radius flush grid, curve-running

The belt consists of plastic hinged links connected by plastic rods. The wide belts are woven together by links that are 102 mm, 124 mm, and 180 mm wide. The assembled belt forms a wide, flat, and tight conveyor surface. Five standard widths of belt can be delivered: 304 mm, 456 mm, and 608 mm.

Standard belt color is white but blue belts can also be ordered.

Belts with polyamide pins are available for dry or semiwet applications. In constant wet applications, belts with acetal pins must be used. This is due to the fact that polyamide pins will absorb water and swell in wet applications, and acetal pins will squeak in dry environments.

Flat top belt, straight running

The belt has a minimal number of seams and has open hinges that are easy to clean. The belt is white and is available with acetal pins for wet applications


Travel direction of the belts:







Flat top belt



Technical characteristics

		,
Belt width	304 mm	
Modular belt weight (Acetal) Radius flush grid (R2.2) Radius flush grid (R1.7) Flat top belt	2,29 kg/m 2,57 kg/m 2,14 kg/m	PO
Modular belt height Radius flush grid Flat top belt	13 mm 10 mm	X70X
Belt pitch	25,4 mm	
Max. permissible belt tension without bends: Max. permissible belt tension through a bend:	1200N 670N/500N*	X85X
*- belt R1.7 (WLTP 1A304 S, WLTP 1A304 BS, WLTP 1A304 WS, WLTP 1A304 WBS)		X180X

		- 1/0001/
Belt width	203 mm	\X300X
Modular belt weight (Acetal) Radius flush grid	1,53 kg/m	WL
Modular belt height Radius flush grid	13 mm	222X
Belt pitch	25,4 mm	WL
Max. permissible belt tension without bends Max. permissible belt tension through a bend:	1200N	273X
Belt width 203	500N	
		WL

Tools and accessories

The belt should be pretensioned with a return slack of about 25 mm. Too much belt slack is a safety risk as the belt can hang below the side of the conveyor beam. A belt $_{
m WI}$ tensioner tool (5118803) is available in order to facilitate 678X installation of the belt and minimize the amount of slack in the return belt.

Ordering information

The belt is delivered in assembled 1 m lengths. To calculate the total length required, remember to add for belt consumed by the idler and drive units.

TR **APX**

WL

526X

CSX

GRX

FSTX

Radius flush grid belt (R2.2), Dry



Plain belt
Belt material Acetal (POM)
Pin material Polyamide (PA),
brown
Length 1 m

304 mm wide, White WLTP 1A304L 304 mm wide, Blue WLTP 1A304L B

Flat top belt



Flat top belt
Belt material Acetal (POM)
Pin material Acetal (POM), white
Length 1 m
304 mm wide

WLTP 1B304 W


Radius flush grid belt (R2.2), Wet



Plain belt
Belt material Acetal (POM)
Pin material Acetal (POM),
white
Length 1 m

304 mm wide, White 304 mm wide, Blue WLTP 1A304L W WLTP 1A304L WB

Radius flush grid belt (R1.7), Dry



Plain belt
Belt material Acetal (POM)
Pin material Polyamide (PA),
brown
Length 1 m
304 mm wide, White
304 mm wide, Blue

WLTP 1A304 S WLTP 1A304 BS

Belt tensioner tool for radius flush grid

Belt tensioner tool 5118803

Radius flush grid belt (R1.7), Wet



Plain belt

Belt material Acetal (POM) Pin material Acetal (PA), white

Length 1 m

304 mm wide, White 304 mm wide, Blue

WLTP 1A304 WS WLTP1A304 WBS

Radius flush grid belt (R2.2), Dry (Spare part only Available as request for quote item)



Plain belt

Belt material Acetal (POM) Pin material Polyamide (PA), brown

Length 1 m

304 mm wide, White 304 mm wide, Blue

WLTP 1A304 WLTP 1A304 B

Note! For use with belt delivered before April 2019

Radius flush grid belt (R2.2), Wet (Spare part only Available as request for quote item)



Plain belt

Belt material Acetal (POM) Pin material Acetal (POM),

white

Length 1 m

304 mm wide, White 304 mm wide, Blue

WLTP 1A304 W WLTP 1A304 WB PO

Note! For use with belt delivered before April 2019

PU

X70X

X85X

X180X

X300X

WL 222X

WL 273X



WL 526X

WL 678X

CSX


GRX

FSTX

TR

APX

Conveyor Beams - Introduction



Conveyor frame structure

Frame profiles and cross bars

In order to facilitate cleaning, the top belt can be lifted up and the outer slide rails can be folded back.

For hygiene reasons, the WLX system is based on an easy-to-clean, free hanging return belt.

Élongation of the belt due to load is normally evenly distributed on the return side and along the whole conveyor, and placement of the belt guides for the return belt is critically important for proper conveyor system performance. Conveyor beams can be ordered from 142 mm up to 3000 mm and are always pre-engineered and configured according to the rules that must be followed.


Conveyor beams are normally not symmetrical, which is why they have an upstream and downstream end. An arrow label on the conveyor beam side indicates the appropriate top belt travel direction to ensure correct assembly.


Components such as plain bends, etc., cannot be placed too close to an End drive unit. Therefore, the minimum permissible length for conveyor beam sections when connecting to an End drive unit is 844 mm. This ensures a sufficient amount of return belt tension directly after the drive sprocket to avoid slack close to the sprocket wheel. The return belt hanging between the first two belt guides provides this belt tension (called back tension). For more information see WLX Engineering guidelines.

Connecting brackets have to be ordered separately when joining End drives, idler ends, conveyor beams, etc.

When joining two conveyor beams, a beam spacer kit must be ordered separately.


Conveyor dimensions





Technical specifications


Minimum permissible conveyor beam length to be connected:







In order to simplify the cleaning process FlexLink can offer belt lift arms for straight conveyors. Contact FlexLink for more information.



P0 X70X

X85X

X180X

X300X

WL 222X

WL 273X

WL 374X

WL 526X

WL 678X

CSX

GRX


FSTX


TR APX


Conveyor frame components













Slide rail





Р0

X70X

X85X

X180X

X300X

WL 222X

WL 273X



WL 526X

WL 678X

CSX

GRX

FSTX

TR

APX



End drive unit

End drive units

Size	Direct drive, no slip clutch				
Drive unit	F, V				

Drive unit types

A soft motor start is recommended for use with highspeed and long conveyors. This is because these types of modular belts are quite heavy, and the free hanging return belt can begin to oscillate momentarily during startup.

A grease nipple is included in all flange bearings. The bearings are initially filled with FDA-approved, foodgrade grease (NSF H1).

End drive units including SEW motors IP 65, can be ordered with food-grade oil and stainless steel hollow shafts in the web-based configurator.

Motor specifications

Motors are available for 230/400 V, 50 Hz and 230/460 V, 60 Hz. Variable speed motors are SEW Movimot, 380–500 V. Note that variable speed motors include a control box that adds 120 mm to the width of the motor.

IP55 available with standard oil.

IP65 available with food grade oil.


Technical specifications

Maximal speed40 m/min Number of teeth on sprocket wheel.... 16

Belt tensioner unit

A belt tensioner unit should always be placed near the End drive unit and its use is recommended:

- for long conveyors >20 meters
- for long conveyors >15 m and a speed of >30 m/min
- for conveyors with frequent starts/stops, especially if the load is high
- if an End drive unit needs to be placed close to a plain bend
- if an End drive unit needs to be placed on the lower part next to a conveyor slope section
- for short conveyors where the belt slack length is insufficient to lift the belt for cleaning



Ordering information

Drive units with motors must be specified using the webbased configurator. The configurator provides detailed information and step-by-step guidance in the specification process. A product code string is generated, containing the specification details. See next page for examples of code strings.

Drive units *without* motors can be ordered using the designations in the catalogue.

- Connecting brackets have to be ordered separately.
- Slide rail must be ordered separately.

Dimension

Note that dimensions relating to drive unit motors depend on the motor specified during the configuration.

Drive units - configuration strings

Below are two examples of text strings obtained from the configurator with explanations.

Drive unit with fixed speed motor

Item no	Α	В	D	E		G	Н	I
	HNP	- L	- V	1 - SA	37 -	50/230	- 0,18kW	- TF

Drive unit with variable speed motor

Item no	Α	В	D	E	F	G	J	K
	HPV	- L -	V6-15	SA37	- MM03	- 50/380-500	- C -	Р

Item no - Drive type

WLEBX: End drive

A - 0-Unit

HNP: Direct drive, no slip clutchV: Variable speed

B – Motor position

L: Left R: Right

D - Speed

V...: Fixed speed... m/min

V... -...: Variable speed range...-... m/min

E - Gearbox

SA37: SEW motor type SA37 WA30: SEW gear box type WA30

F - Movimot size

MM03: SEW Movimot type, 0,37 kW MM05: SEW Movimot type, 0,55 kW MM07: SEW Movimot type, 0,75 kW (position is omitted for fixed speed motors)

G – Electrical environment

50/230: 50 Hz, 230 V 50/400: 50 Hz, 400 V 60/230: 60 Hz, 230 V 60/460: 60 Hz, 460 V

50/380-500: SEW Movimot variable speed motor

H – Motor power

... kW: Motor power, kW (position is omitted for variable speed motors see position F)

I – Thermal protection

No: No thermal protection

TF: Thermal protection type TF TH: Thermal protection type TH

(position is omitted for variable speed motors)

J - Hybrid cable

No: No hybrid cable

C: Hybrid cable included in SEW Movimot (position is omitted for fixed speed motors)

K - Fieldbus

No: No fieldbus

P: Profibus fieldbus, maintenance switch D: DeviceNet fieldbus, maintenance switch (position is omitted for fixed speed motors) P0

X70X

X85X

X180X

X300X

WL 222X

WL 273X



WL 526X

WL 678X

CSX

GRX

OI I


FSTX

TR APX

IDX

אטו

End drive unit, Easy Clean, Radius flush grid 374



End drive unit

Fixed/variable speed*
Without motor:

Transmission on left side Transmission on right side


WLEBX A374

WLEBX0A374NLP WLEBX0A374NRP

* Use online configurator when ordering Effective track length: 0,80 m Weight, incl belt: 16 kg

Belt tensioner unit Belt tensioner for: WL374X 5118891

End drive unit, Easy Clean, Flat top 374



End drive unit

Fixed/variable speed*
Without motor:

Transmission on left side Transmission on right side **WLEBX B374**


WLEBX0B374NLP WLEBX0B374NRP

* Use online configurator when ordering Effective track length: 0,80 m Weight, incl belt: 16 kg

End drive unit S, Radius flush grid 374

Required extra belt length

Weight, incl belt: 16 kg



End drive unit


Fixed/variable speed* Without motor:

Transmission on left side Transmission on right side **WLEBX A374 S**

0,55 m

WLEBX0A374NLP S WLEBX0A374NRP S

* Use online configurator when ordering Effective track length: 0,75 m Weight, incl belt: 15,3 kg



P0

X70X

X85X

X180X

X300X

WL 222X

WL 273X



WL 526X

WL 678X


CSX

GRX

FSTX

TR

APX



Idler end unit (generic picture)


Chain guidance at end of conveyor


The idler end unit is used to guide the chain from the return side of the conveyor up to the top side with a minimum of friction. The chain is guided by two or more idler wheels on a common, rotating shaft supported by ball bearings.

Ordering information

- Connecting strips are included with the idler end units.
- Slide rail must be ordered separately.


Idler units








When using radius flush grid belts in plain bends, the belt pull force will be concentrated on the outer part of the belt. A certain straight section is needed before and after the bend in order to transfer the load between the outer belt section and evenly distribute it to the straight belt section. This is critical before entering another plain bend, end drive unit, etc. This required straight section is always integrated in the plain bend itself (300 mm for WL374X, 450 mm for WL526X, and 600 mm for WL678X).

Plain bend placement, as for all other Flexlink conveyors, should always be considered. A plain bend placed too far downstream on a conveyor generates unnecessary belt pull. Also, placement of a plain bend too close to an end drive unit can lead to an unnecessary slack increase and a separate slack unit must be added. Always use the Flexlink calculation tool (FLCT) to calculate the resulting pull forces.












Plain bend, 90°±1° R=820±10 mm

WLBPX 90A374

* Use online configurator when ordering Effective track length: 4,3 m Weight, incl belt: 51 kg









Weight, incl belt: 29 kg


Plain bend, Easy Clean 90°, R1,7 Plain bend, 90°±1° R=669±10 mm * Use online configurator when ordering Effective track length: 3,3m

Weight, incl belt: 40,5 kg



Vertical bends







WL 526X

WL 678X

CSX

GRX

FSTX


TR


APX

Support System Modules - Introduction

Conveyor supports


Support modules must be specified using the web-based configurator. There, a product code string is generated that contains the specification details (E.g., WLUFX S01-WL374X-900).






XCFSX 16x80 A

WLCSX 10X56





Bracket type: